

VSM10 SERIES



VSM1087



应用领域 Application

安防监控设备、CCTV镜头、IT产业、精密仪器
Security monitoring equipment, CCTV lens, IT industry, precision instruments

型号 ITEM NUMBER	额定电压 RATED VOLTAGE	电阻 RESISTANCE	驱动方式 DRIVE MODE	步距角 STEP ANGLE	最大自启动周波数 MAX. SELF-START FREQUENCY	最大连续响应周波数 MAX CONTINUOUS RESPONSE FREQUENCY	引入力矩 INTRODUCING TORQUE	脱出力矩 TRIPPING TORQUE
VSM1087	5.0V	18 ±10%Ω	2-2	18°	300 PPS(min)	800 PPS(min)	2.8gf-cm(min)	3.8gf-cm(min)
VSM1068	5.0V	55 ±10%Ω	2-2	18°	1000 PPS(min)	1800 PPS(min)	2.0gf-cm(min)	2.2gf-cm(min)

规格参考 Specification

CONNECTION DIAGRAM



SEQUENCE OF EXCITATION				
STEP	1	2	3	4
A	+	+	-	-
\bar{A}	-	-	+	+
B	-	+	+	-
\bar{B}	+	-	-	+

OUTPUT SHAFT ROTATION CW

