

STEPPING MOTOR 步进电机

VSM10 SERIES



VSM1070



应用领域 Application

CCTV监控器、票据打印机、办公自动化、智能家居设备、IT产业、精密仪器

CCTV monitors, bill printers, office automation, smart home appliances, IT industry, precision instruments

型号 ITEM NUMBER	额定电压 RATED VOLTAGE	电阻 RESISTANCE	驱动方式 DRIVE MODE	步距角 STEP ANGLE	最大自启动周波数 MAX. SELF-START FREQUENCY	最大连续响应周波数 MAX CONTINUOUS RESPONSE FREQUENCY	引入力矩 INTRODUCING TORQUE	脱出力矩 TRIPPING TORQUE
VSM1070	5.0V	40 ±10%Ω	2-2	18°	1000 PPS(min)	1800 PPS(min)	4.5gf-cm(min)	5.0gf-cm(min)
VSM1094	5.0V	40 ±10%Ω	2-2	18°	800 PPS(min)	1200 PPS(min)	4.0gf-cm(min)	5.0gf-cm(min)

规格参考 Specification

CONNECTION DIAGRAM



SEQUENCE OF EXCITATION				
STEP	1	2	3	4
A	+	+	-	-
\bar{A}	-	-	+	+
B	-	+	+	-
\bar{B}	+	-	-	+

OUTPUT SHAFT ROTATION CW

